

RE-717M

Analogue Addressable Manual Call Point



Product Overview

The RE-717M Manual Call Point is compliant with latest standards and is designed to interface with Ravel make addressable fire alarm panel, Avani.DIP switches are provided for addressing of the call point. The RED blinking LED indicates normal operating condition. Activation of MCP is indicated by RED steady LED, and also a visible YELLOW-BLACK strip.



Features:

- EN54-11 Approved Type A Indoor Use.
- Re-Settable by an element kit.
- Suitable for flush or surface mounting
- Module Addressing by 8 way DIP Switches.
- Low Standby Current.


Mechanical Specification:

Temperature	:	0 - 49 °C
Relative Humidity	:	0 - 93% non-condensing
Connection	:	2.5mm ² Max.
Weight	:	125g.
IP Rating	:	IP 53
Dimension	:	92mm X 92mm X 48 mm

Electrical Specification

Operating Voltage	:	24VDC.
Power-up surge current	:	0.8mA
Quiescent Current	:	0.5mA.
Alarm Current	:	5.8mA

Wiring Diagram



Note:-

L1 and L2 are polarity insensitive, but for the sake of consistency. It's recommend the L2 kept negative

Ordering Information:

Model	Description
RE-717M	Analogue Addressable Manual Call Point

India:

RAVEL ELECTRONICS PVT LTD.,
(An ISO 9001 Company)
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.
E-Mail: marketing@ravelfire.com; Web : www.ravelfire.com

United Kingdom:

RAVEL ELECTRONICS LTD.,
Unit 11, Chancel Industrial Estate, Newhall street,
Willenhall WV13 1NX, West Midlands, United Kingdom.
E-mail: info@ravelfire.co.uk ;Web: www.ravelfire.co.uk